

# PS-1290 12 Volt 9.0 AH

**Rechargeable Sealed Lead Acid Battery** 




We've Got The Power.™






### Terminals: in (mm)

- F2 Quick disconnect tabs, 0.250" x 0.032"
  - Mate with AMP. INC FASTON "250" series
- NB Tin plated brass posts with nut & bolt fasteners



# Physical Dimensions: in (mm)





F2: L: 5.95 (151) W: 2.56 (65) H: 3.70 (94) HT: 3.86 (98)

NB: L: 5.95 (151) W: 2.56 (65) H: 3.70 (94) HT: 4.15 (106)

Tolerances are +/- 0.04 in. (+/- 1mm) and +/- 0.08 in. (+/- 2mm) for height dimensions. All data subject to change without notice.

### **Features**

- Absorbent Glass Mat (AGM) technology for superior performance
- Valve regulated, spill proof construction allows safe operation in any position
- Power/volume ratio yielding unrivaled energy density
- Rugged impact resistant ABS case and cover (UL94-HB)
- Approved for transport by air. D.O.T., I.A.T.A., F.A.A. and C.A.B. certified
- U.L. recognized under file number MH 20845


# **Performance Specifications**

	<u>-</u>	
Nominal Voltage		
Nominal Capacity		
20-hr.	(450mA to 10.50 volts)	9.00 AH
10-hr.	(810mA to 10.50 volts)	8.10 AH
5-hr.	(1.44A to 10.20 volts)	7.20 AH
1-hr.	(5.4A to 9.00 volts)	5.40 AH
15-min	. (14.4A to 9.00 volts)	3.60 AH
Approximate Weight		6.00 lbs. (2.72 kg)
Energy Density (20-hr. rate) 1.92 W-h/in3 (116.94 W		
Specific Energy (20-hr. rate) 18		18.00 W-h/lb (39.68 W-h/kg)
Internal Resistance (approx.)		13 milliohms
Max Discharge Current (7 Min.)		
Max Short-Duration Discharge Current (10 Sec.) 90.0 amperes		
Shelf Life (% of nominal capacity at 68°F (20°C)		
1 Month		97%
3 Mont	hs	91%
6 Mont	hs	83%
Operating Temperature Range		
Charge	· · · · · · · · · · · · · · · · · · ·	4°F (-20°C) to 122°F (50°C)
Dischai	rge	40°F (-40°C) to 140°F (60°C)


Power-Sonic Chargers......PSC-12800A, 12800A-C



### Shelf Life & Storage



## Discharge Time vs. Discharge Current



# Charging

Cycle Applications: Limit initial current to 2.7A. Charge until battery voltage (under charge) reaches 14.4 to 14.7 volts at 68°F (20°C). Hold at 14.4 to 14.7 volts until current drops to under 90mA. Battery is fully charged under these conditions, and charger should be disconnected or switched to "float" voltage.


"Float" or "Stand-By" Service: Hold battery across constant voltage source of 13.5 to 13.8 volts continuously. When held at this voltage, the battery will seek its own current level and maintain itself in a fully charged condition.

Note: Due to the self-discharge characteristics of this type of battery, it is imperative that they be charged within 6 months of storage, otherwise permanent loss of capacity might occur as a result of sulfation.


### Chargers

Power-Sonic offers a wide range of chargers suitable for batteries up to 100AH. Please refer to the Charger Selection Guide in our specification sheets for "C-Series Switch Mode Chargers" and "Transformer Type A and F Series". Please contact our Technical department for advice if you have difficulty in locating suitable models.


### Discharge Characteristics



### Life Characteristics in Stand-By Use



### Life Characteristics in Cyclic Use



### **Further Information**

Please refer to our website www.power-sonic.com for a complete range of useful downloads, such as product catalogs, material safety data sheets (MSDS), ISO certification, etc..

### **Distributor** in Mexico

Plan de San Luis № 398 Col. Nueva Santa María C.P. 02800 Azcapotzalco, Ciudad de México Tels: 01(55) 9172-4906 / 07 Fax: 5355-6033 info@power-all.com